



REVISION HISTORY

<u>Revision</u>	<u>Description</u>	<u>Issue Date</u>
Rev. 0.1	Initial Issue	May 30.2007
Rev. 0.11	Modify product name rule	Oct. 11.2007
Rev. 0.12	Modify Thermal shutdown Protection	Nov. 26.2007
Rev. 0.13	Add out power protection	March 14.2008
Rev. 0.14	Modify application circuit	March 15.2008
Rev. 1.0	Release datasheet	March 26.2008
Rev. 1.1	Add Typical performance characteristics	Aug. 19. 2008



FEATURES

- 1.4 W Into 8Ω from 5V power supply at THD = 10% (Typ.).
- 2.5V~5.5V Power supply.
- Low shutdown current.
- Low quiescent current.
- Minimum external components.
- No output filter required for inductive loads.
- Output Pin Short-Circuit Protection (Short to Output Pin, Short to GND, Short to VDD).
- Low noise during turn-on and turn-off transitions.
- Lead free and green package available. (RoHS Compliant)
- 8-pin MSOP package.

APPLICATION

- Portable electronic devices
- Mobile Phones
- PDAs

GENERAL DESCRIPTION


The LY8005 is a high efficiency, 1.4 W mono class D audio power amplifier. It is a low noise, filterless PWM architecture eliminates the output filter, reducing external component count, system cost, and simplify design.

The LY8005 is designed to meet of mobile phones and other portable electronic devices. The LY8005 is a single 5V supply, it is capable of driving 8Ω speaker load at a continuous average output of 1.4 W with 10% THD+N. The LY8005 has high efficiency with speaker loads compared to a typical Class AB amplifier. With a 3.6V supply driving an 8Ω speaker, the LY8005 efficiency for a 400mW power level is 88%.

In cellular handsets, the earpiece, speaker phone, and melody ringer can each be driven by the LY8005. The gain of the LY8005 is externally configurable which allows independent gain control from multiple sources by summing the signals. Output short circuit and thermal overload protection prevent the device from damage during fault conditions.

PIN CONFIGURATION

8 Pin MSOP Package (TOP VIEW)





PIN DESCRIPTION

SYMBOL	Pin No.	DESCRIPTION
SHUTDOWN	1	Shutdown the device.(when low level is active the pin)
NC	2	No internal connection
+IN	3	Positive input
-IN	4	Negative input
Vo+	5	Positive BTL output
V _{DD}	6	Power supply
GND	7	Ground
Vo2	8	Negative BTL output

ORDERING INFORMATION

LY 8 005 V W

W : Lead Information

L : Green

F : Pb Free

V : Package Type

U : 8-Pin MSOP

Product Name

A : Product Line

LY : Lyontek Product Number Prefix

APPLICATION CIRCUIT




Figure 1. Application Schematic With Differential Input Configuration




Figure 2. Application Schematic With Differential and Capacitors Input Configuration




Figure 3. Application Schematic With Single-Ended Input

ABSOLUTE MAXIMUM RATINGS*

PARAMETER	SYMBOL	RATING	UNIT
Supply Voltage	V_{DD}	6.0	V
Operating Temperature	T_A	0 to 70 (C grade)	
		-20 to 80 (E grade)	
		-40 to 85 (I grade)	
Input Voltage	V_I	-0.3V to $V_{DD} + 0.3V$	V
Storage Temperature	T_{STG}	-65 to 150	
Power Dissipation	P_D	Internally Limited	W
ESD Susceptibility	V_{ESD}	2000	V
Junction Temperature	T_{JMAX}	150	
Soldering Temperature (under 10 sec)	T_{SOLDER}	260	

*Stresses greater than those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to the absolute maximum rating conditions for extended period may affect device reliability.



ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$, Unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output offset voltage (measured differentially)	$ V_{OS} $	$V_I = 0\text{ V}$, $A_v = 2\text{ V/V}$, $V_{DD} = 2.5\text{ V to } 5.5\text{ V}$	-	-	25	mV
High-level input current	$ I_{IH} $	$V_{DD} = 5.5\text{ V}$, $V_I = 5.8\text{ V}$	-	-	100	μA
Low-level input current	$ I_{IL} $	$V_{DD} = 5.5\text{ V}$, $V_I = 0.3\text{ V}$	-	-	5	μA
Power supply rejection ratio	PSRR	$V_{DD} = 2.5\text{ V to } 5.5\text{ V}$		-75	-55	dB
Common mode rejection ratio	CMRR	$V_{DD}=2.5\text{V to } 5.5\text{V}$, $V_{IC} = V_{DD}/2\text{ to } 0.5\text{ V}$, $V_{IC} = V_{DD}/2\text{ to } V_{DD}-0.8\text{ V}$,		-60	-48	dB
Quiescent Current	I_Q	$V_{DD} = 5.5\text{V}$, No Load	-	3.4	4.5	mA
		$V_{DD} = 3.6\text{V}$, No Load	-	2.8	-	
		$V_{DD} = 2.5\text{V}$, No Load	-	2.2	3.2	
Shutdown Current	I_{SD}	$V_{SHUTDOWN} = 0.8\text{V}$, $V_{DD} = 2.5\text{V to } 5.5\text{V}$	-	0.3	2	μA

OPERATING CHARACTERISTICS ($T_A = 25^\circ\text{C}$, Gain = 2 V/V , $R_L = 8\Omega$, Unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITION		MIN.	TYP.	MAX.	UNIT
Out Power	P _O	THD+N= 1%, f = 1 kHz, R _L = 8Ω	V _{DD} =5V	-	1.1	-	W
			V _{DD} =3.6V	-	0.64	-	
			V _{DD} =2.5V	-	0.3	-	
		THD+N= 10%, f = 1 kHz, R _L = 8Ω	V _{DD} =5V	-	1.5	-	W
			V _{DD} =3.6V	-	0.79	-	
			V _{DD} =2.5V	-	0.37	-	
Total harmonic distortion + noise	THD+N	P _O = 1 W, f = 1 kHz, R _L = 8Ω	V _{DD} =5V	-	0.15	-	%
		P _O = 0.5 W, f = 1 kHz, R _L = 8Ω	V _{DD} =3.6V	-	0.18	-	
		P _O = 0.2 W, f = 1 kHz, R _L = 8Ω	V _{DD} =2.5V	-	0.12	-	
Supply ripple rejection ratio	K _{SVR}	f = 217 Hz, V(RIPPLE) = 200mVpp, inputs ac-grounded with C _i = 2uF	V _{DD} =3.6V	-	-71	-	dB
Signal-to-noise ratio	SNR	P _O = 1 W, R _L = 8Ω	V _{DD} =5V	-	97	-	dB
Output voltage noise	V _n	V _{DD} = 3.6 V, f = 20 Hz to 20 kHz, Inputs ac-grounded with C _i = 2 μF	No weighting	-	48	-	μV _{RMS}
			A weighting	-	36	-	
Common mode rejection ratio	CMRR	V _{IC} = 1 V _{pp} , f = 217 Hz	V _{DD} =3.6V	-	-63	-	dB
Start-up time from shutdown	Z _I	V _{DD} = 3.6 V		-	1	-	ms

TYPICAL PERFORMANCE CHARACTERISTICS

Figure 4
Total Harmonic Distortion + Noise vs Frequency




Figure 5
Total Harmonic Distortion + Noise vs Output Power




Figure 6
Efficiency vs Output power ($R_L=8\Omega$, $33\mu H$)




Figure 7
Power dissipation vs Output power ($R_L=8\Omega$, $33\mu H$)




Figure 8
Supply Current vs Output Power ($R_L=8\Omega$, 33 μ H)




Figure 9
Output Power vs Load Resistance (P_O at 10 % THD with f = 1 kHz)




Figure 10
Output Power vs Load Resistance (Po at 1 % THD with f = 1 kHz)




Figure 11
THD+N & Output Power vs Temperature (VDD=3V, RL=8 Ω)




Figure 12
THD+N & Output Power vs Temperature (VDD=4.5V, RL=8)




Figure 13
THD+N & Output Power vs Temperature (VDD=5.0V, RL=8)




Figure 14
FCC Class-B (Vertical)




Figure 15
FCC Class-B (Horizontal)




Figure 16
CISPR Class-B (Vertical)





Figure 17
CISPR Class-B (Horizontal)





APPLICATION INFORMATION

Fully Differential Amplifier

The LY8005 is a fully differential amplifier with differential inputs and outputs. The fully differential amplifier consists of a differential amplifier and a common-mode amplifier. The differential amplifier ensures that the amplifier outputs a differential voltage on the output that is equal to the differential input times the gain. The common-mode feedback ensures that the common-mode voltage at the output is biased around $V_{DD}/2$ regardless of the common-mode voltage at the input. The fully differential LY8005 can still be used with a single-ended input; however, the LY8005 should be used with differential inputs when in a noisy environment, like a wireless handset, to ensure maximum noise rejection.

Advantages of Fully Differential Amplifiers

Input-coupling capacitors not required:

The fully differential amplifier allows the inputs to be biased at voltage other than mid-supply. For example, if a codec has a midsupply lower than the midsupply of the LY8005, the common-mode feedback circuit will adjust, and the LY8005 outputs will still be biased at midsupply of the LY8005. The inputs of the LY8005 can be biased from 0.5 V to $V_{DD} - 0.8$ V. If the inputs are biased outside of that range, input - coupling capacitors are required.

Midsupply bypass capacitor, $C_{(BYPASS)}$, not required:

The fully differential amplifier does not require a bypass capacitor. This is because any shift in the midsupply affects both positive and negative channels equally and cancels at the differential output.

Better RF-immunity:

GSM handsets save power by turning on and shutting off the RF transmitter at a rate of 217 Hz. The transmitted signal is picked-up on input and output traces. The fully differential amplifier cancels the signal much better than the typical audio amplifier.

Component Selection

Figure 1 shows the LY8005 typical schematic with differential inputs and Figure 2 shows the LY8005 with differential and capacitors inputs, and Figure 3 shows the LY8005 with single-ended inputs. Differential inputs should be used whenever possible because the single-ended inputs are much more susceptible to noise.

Table 1. Typical Component Values

Ref Des	Value
R_I	150k Ω ($\pm 0.5\%$)
C_S	1 μ F(+22%,-80%)
C_I (1)	3.3nF ($\pm 10\%$)

(1) C_I is only needed for single-ended input or if V_{ICM} is not between 0.5 V and $V_{DD} - 0.8$ V. $C_I = 3.3$ nF (with $R_I = 150$ k Ω) gives a high-pass corner frequency of 321 Hz.



Input Resistors (R_I)

The input resistors (R_I) set the gain of the amplifier according to equation Equation 1.

$$\text{Gain} = \frac{2 \times 150 \text{ k}\Omega}{R_I} \dots\dots\dots(1)$$

Resistor matching is very important in fully differential amplifiers. The balance of the output on the reference voltage depends on matched ratios of the resistors. CMRR, PSRR, and cancellation of the second harmonic distortion diminish if resistor mismatch occurs. Therefore, it is recommended to use 1% tolerance resistors or better to keep the performance optimized. Matching is more important than overall tolerance. Resistor arrays with 1% matching can be used with a tolerance greater than 1%. Place the input resistors very close to the LY8005 to limit noise injection on the high-impedance nodes. For optimal performance the gain should be set to 2 V/V or lower. Lower gain allows the LY8005 to operate at its best, and keeps a high voltage at the input making the inputs less susceptible to noise.

Decoupling Capacitor (C_s)

The LY8005 is a high-performance class-D audio amplifier that requires adequate power supply decoupling to ensure the efficiency is high and total harmonic distortion (THD) is low. For higher frequency transients, spikes, or digital hash on the line, a good low equivalent-series-resistance (ESR) ceramic capacitor, typically 1 μF, placed as close as possible to the device V_{DD} lead works best. Placing this decoupling capacitor close to the LY8005 is very important for the efficiency of the class-D amplifier, because any resistance or inductance in the trace between the device and the capacitor can cause a loss in efficiency. For filtering lower-frequency noise signals, a 10 μF or greater capacitor placed near the audio power amplifier would also help, but it is not required in most applications because of the high PSRR of this device.

Input Capacitors (C_I)

The LY8005 does not require input coupling capacitors if the design uses a differential source that is biased from 0.5 V to V_{DD} - 0.8 V (shown in Figure 1). If the input signal is not biased within the recommended common-mode input range, if needing to use the input as a high pass filter (shown in Figure 2), or if using a single-ended source (shown in Figure 3), input coupling capacitors are required. The input capacitors and input resistors form a high-pass filter with the corner frequency, f_c, determined in equation Equation 2.

$$f_c = \frac{1}{2 R_I C_I} \dots\dots\dots(2)$$

The value of the input capacitor is important to consider as it directly affects the bass (low frequency) performance of the circuit. Speakers in wireless phones cannot usually respond well to low frequencies, so the corner frequency can be set to block low frequencies in this application. Equation Equation 3 is reconfigured to solve for the input coupling capacitance.

$$C_I = \frac{1}{2 R_I f_c} \dots\dots\dots(3)$$



If the corner frequency is within the audio band, the capacitors should have a tolerance of $\pm 10\%$ or better, because any mismatch in capacitance causes an impedance mismatch at the corner frequency and below. For a flat low-frequency response, use large input coupling capacitors ($1\ \mu\text{F}$). However, in a GSM phone the ground signal is fluctuating at 217 Hz, but the signal from the codec does not have the same 217 Hz fluctuation. The difference between the two signals is amplified, sent to the speaker, and heard as a 217 Hz hum.

Summing Input Signals With The LY8005

Most wireless phones or PDAs need to sum signals at the audio power amplifier or just have two signal sources that need separate gain. The LY8005 makes it easy to sum signals or use separate signal sources with different gains. Many phones now use the same speaker for the earpiece and ringer, where the wireless phone would require a much lower gain for the phone earpiece than for the ringer. PDAs and phones that have stereo headphones require summing of the right and left channels to output the stereo signal to the mono speaker.

Summing Two Differential Input Signals

Two extra resistors are needed for summing differential signals (a total of 5 components). The gain for each input source can be set independently (see equations Equation 4 and Equation 5, and Figure 18).

$$\text{Gain 1} = \frac{V_o}{V_{i1}} = 2 \times \frac{150\text{k}\Omega}{R_{i1}} \dots\dots\dots(4)$$

$$\text{Gain 2} = \frac{V_o}{V_{i2}} = 2 \times \frac{150\text{k}\Omega}{R_{i2}} \dots\dots\dots(5)$$

If summing left and right inputs with a gain of 1 V/V, use $R_{i1} = R_{i2} = 300\ \text{k}\Omega$

If summing a ring tone and a phone signal, set the ring-tone gain to Gain 2 = 2 V/V, and the phone gain to gain 1 = 0.1 V/V. The resistor values would be. . .

$R_{i1} = 3\ \text{M}\Omega$, and $R_{i2} = 150\ \text{k}\Omega$.




Figure 18. Application Schematic With LY8005 Summing Two Differential Input

Summing a Differential Input Signal and a Single-Ended Input Signal

Figure 19 shows how to sum a differential input signal and a single-ended input signal. Ground noise can couple in through IN+ with this method. It is better to use differential inputs. The corner frequency of the single-ended input is set by C_{i2}, shown in equation Equation 8. To assure that each input is balanced, the single-ended input must be driven by a low-impedance source even if the input is not in use.

$$\text{Gain 1} = \frac{V_o}{V_{i1}} = 2 \times \frac{150\text{k}\Omega}{R_{i1}} \quad (6)$$

$$\text{Gain 2} = \frac{V_o}{V_{i2}} = 2 \times \frac{150\text{k}\Omega}{R_{i2}} \quad (7)$$

$$C_{i2} = \frac{1}{2 R_{i2} f_{c2}} \quad (8)$$

If summing a ring tone and a phone signal, the phone signal should use a differential input signal while the ring tone might be limited to a single-ended signal. Phone gain is set at gain 1 = 0.1 V/V, and the ring-tone gain is set to gain 2 = 2 V/V, the resistor values would be ...

$R_{i1} = 3 \text{ M}\Omega$, and $R_{i2} = 150 \text{ k}\Omega$.

The high pass corner frequency of the single-ended input is set by C_{i2}. If the desired corner frequency is less than 20 Hz.

$$C_{i2} > \frac{1}{2 \cdot 150k\Omega \cdot 20Hz} \dots\dots\dots(9)$$

$$C_{i2} > 53pF \dots\dots\dots(10)$$




Figure 19. Application Schematic With LY8005 Summing Differential and Sing-Ended Input

Summing Two Single-Ended Input Signals

Four resistors and three capacitors are needed for summing single-ended input signals. The gain and corner frequencies (f_{c1} and f_{c2}) for each input source can be set independently (see equations Equation 11 through Equation 14, and Figure 20). Resistor, R_P , and capacitor, C_P , are needed on the $IN+$ terminal to match the impedance on the $IN-$ terminal. The single-ended inputs must be driven by low impedance sources even if one of the inputs is not outputting an ac signal.

$$\text{Gain 1} = \frac{V_o}{V_{i1}} = 2 \times \frac{150k\Omega}{R_{i1}} \dots\dots\dots(11)$$

$$\text{Gain 2} = \frac{V_o}{V_{i2}} = 2 \times \frac{150k\Omega}{R_{i2}} \dots\dots\dots(12)$$

$$C_{i1} = \frac{1}{2 \cdot R_{i1}f_{c1}} \dots\dots\dots(13)$$

$$C_{I2} = \frac{1}{2 R_{I2} f_{c2}} \dots (14)$$

$$C_P = C_{I1} + C_{I2} \dots (15)$$

$$R_P = \frac{R_{I1} \times R_{I2}}{R_{I1} + R_{I2}} \dots (16)$$






Figure 20. Application Schematic With LY8005 Summing Two Single-ended Input

PACKAGE OUTLINE DIMENSION

8 pin 25.6 mil MSOP Package Outline Dimension



SYMBOLS	MIN.	NOM.	MAX.
A	—	—	1.10
A1	0.00	—	0.15
A2	0.75	0.85	0.95
D	3.00 BSC		
E	4.90 BSC		
E1	3.00 BSC		
L	0.40	0.60	0.80
L1	0.95 REF		
θ°	0	—	8

UNIT : MM

NOTES:

1. JEDEC OUTLINE : MO-187 AA
2. DIMENSION 'D' DOES NOT INCLUDE MOLD FLASH, PROTRUSIONS OR GATE BURRS. MOLD FLASH, PROTRUSIONS OR GATE BURRS SHALL NOT EXCEED 0.15 PER SIDE.
3. DIMENSION 'E1' DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSION. INTERLEAD FLASH OR PROTRUSION SHALL NOT EXCEED 0.25 PER SIDE.
4. DIMENSION '0.22' DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION SHALL BE 0.08 MM TOTAL IN EXCESS OF THE '0.22' DIMENSION AT MAXIMUM MATERIAL CONDITION. DAMBAR CANNOT BE LOCATED ON THE LOWER RADIUS OF THE FOOT. MINIMUM SPAC BETWEEN PROTRUSION AND ADJACENT LEAD IS 0.07 MM.
5. DIMENSIONS 'D' AND 'E1' TO BE DETERMINED AT DATUM PLANE B.

